

## таблица селективности DMX<sup>3</sup> / DPX<sup>3</sup>, DPX

### ■ Пределы селективности (средние значения (кА) при 400 В~)

Нижестоящий автоматический выключатель в литом корпусе	In	Вышестоящий воздушный автоматический выключатель																									
		DMX <sup>3</sup> - N 2500 (50 кА)					DMX <sup>3</sup> - H 2500 (65 кА)					DMX <sup>3</sup> - L 2500 (100 кА)					DMX <sup>3</sup> -N 4000 (50 кА)		DMX <sup>3</sup> -H 4000 (65 кА)		DMX <sup>3</sup> -L 4000 (100 кА)						
		800	1000	1250	1600	2000	2500	800	1000	1250	1600	2000	2500	800	1000	1250	1600	2000	2500	3200	4000	3200	4000	3200	4000		
DPX <sup>3</sup> 160 (16, 25, 36, 50 кА) с или без диф. защиты	16	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T		
	25	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	40	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	63	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	80	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	100	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	125	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
DPX <sup>3</sup> 250 с термомангнитным расцепителем (25, 36, 50 кА), с или без диф. защиты	160	T	T	T	T	T	88	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	100	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	160	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	200	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
DPX <sup>3</sup> 250 с термомангнитным расцепителем (70 кА), с или без диф. защиты	250	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	100	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	160	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	200	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
DPX <sup>3</sup> 250 с электронным расцепителем <sup>(1)</sup> (25, 36, 50 кА), с или без диф. защиты	250	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	40	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	100	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	160	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
DPX <sup>3</sup> 250 с электронным расцепителем <sup>(1)</sup> (70 кА), с или без диф. защиты	200	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	250	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	40	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	100	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
DPX <sup>3</sup> 250 с электронным расцепителем <sup>(2)</sup> (25, 36, 50 кА), с или без диф. защиты	160	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	200	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	250	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	40	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
DPX <sup>3</sup> 250 с электронным расцепителем <sup>(2)</sup> (70 кА), с или без диф. защиты	100	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	160	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	200	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	250	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
DPX с термомангнитным расцепителем (36 кА)	40	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	63	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	100	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	160	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
DPX-H 250 с термомангнитным расцепителем (70 кА)	200	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	250	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
	40	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	63	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
DPX 250 с электронным расцепителем <sup>(1)</sup> S1 и S2 (36 кА)	100	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	160	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	250	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	40	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	
DPX 250 с электронным расцепителем <sup>(2)</sup> S1 и S2 (36 кА)	100	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	160	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	250	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	40	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
DPX-H 250 с электронным расцепителем <sup>(1)</sup> S1 и S2 (70 кА)	100	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	160	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	250	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	40	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
DPX-H 250 с электронным расцепителем <sup>(2)</sup> S1 и S2 (70 кА)	100	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	160	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	250	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
	40	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	
DPX 630 с термомангнитным расцепителем (36 кА)	250	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T
	320	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T
	400	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T
	500	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T
DPX-H 630 с термомангнитным расцепителем (70 кА)	630	-	T	T	T	T	T	-	T	T	T	T	-	T	T	T	T	T	T	T	T	T	T	T	T	T	T
	250	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
	320	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
	400	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
DPX с электронным расцепителем <sup>(1)</sup> S1 и S2 (36 кА)	500	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
	630	-	T	T	T	T	T	-	T	T	T	T	-	T	T	T	T	T	T	T	T	T	T	T	T	T	T
	250	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T
	400	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T	T
DPX-H 630 с электронным расцепителем <sup>(1)</sup> S1 и S2 (70 кА)	630	-	T	T	T	T	T	-	T	T	T	T	-	T	T	T	T	T	T	T	T	T	T	T	T	T	T
	250	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
	400	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
	630	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
DPX-H 630 с электронным расцепителем <sup>(2)</sup> S1 и S2 (70 кА)	250	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
	400	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
	630	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
	800	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
DPX с термомангнитным расцепителем (50 кА)	1000	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
	1250	-	-	-	-	-	T	T	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
	800	-	-	-	-	-	-	-	-	-	-	-	-	-	T	T	T	T	T	T	T	T	T	T	T	T	T
DPX-H 1250 с термомангнитным расцепителем (70 кА)	1000	-	-	-	-																						